

**Generating set with HONDA air cooled petrol engine.**



**2,2-7kVA**  
**50Hz - 3000/min 4 Stroke**



EP2500/11 - EP3300/11



EP6000E/25

| TYPE        | kVA max. | kVA cont. | Amp.      |           | Engine HONDA | HP  | cm <sup>3</sup> | Tank (l) | Autonomy (h at 75% load) | Version                | Dimens. (cm) | kg  | dB(A) @ 7m | LWA |
|-------------|----------|-----------|-----------|-----------|--------------|-----|-----------------|----------|--------------------------|------------------------|--------------|-----|------------|-----|
|             |          |           | 1 ~ 230 V | 3 ~ 400 V |              |     |                 |          |                          |                        |              |     |            |     |
| EP2500/11   | 2,2      | 2         | 9         | -         | GX160        | 5,5 | 163             | 11       | 11,0                     | A-F-FG-O-R-Th          | 58x42x50     | 45  | 66         | 91  |
| EP3300/11   | 3        | 2,7       | 12        | -         | GX200        | 6,5 | 196             | 11       | 8,5                      | A-F-FG-O-R-Th          | 58x42x50     | 50  | 66         | 91  |
| EP4100/25   | 4        | 3,6       | 16        | -         | GX270        | 9   | 270             | 25       | 12,5                     | A-AC-F-FG-h-O-R-TM-V   | 75x60x59     | 77  | 70         | 95  |
| EP6000/25   | 6        | 5,4       | 23        | -         | GX390        | 13  | 389             | 25       | 10,4                     | A-AC-F-FG-h-O-R-TM-V   | 75x60x59     | 92  | 71         | 96  |
| EP6000E/25  | 6        | 5,4       | 23        | -         | GX390        | 13  | 389             | 25       | 10,4                     | A-AC-E-F-FG-h-O-R-TM-V | 75x60x59     | 105 | 71         | 96  |
| EP6500T/25  | 7        | 6,5       | 18        | 8         | GX390        | 13  | 389             | 25       | 10,4                     | AC-B-F-FG-h-O-R-TM-V   | 80x58x63     | 97  | 71         | 96  |
| EP6500TE/25 | 7        | 6,5       | 18        | 8         | GX390        | 13  | 389             | 25       | 10,4                     | AC-B-E-F-FG-h-O-R-TM-V | 80x58x63     | 110 | 71         | 96  |

EP-SH/0206/5T

- A = 2 Sockets 230V - 16A
- AC = automatic choke
- B = 1 Socket 230V - 16A + 1 Socket CEE 400V - 16A 5-pole
- E = Electric Start (Battery included)
- F = Frame
- FG = Mechanical fuel level meter
- h = Hour counter
- O = Oil guard
- R = Recoil Starter
- Th = Circuit breaker
- TM = Thermal Magnetic breaker
- V = Voltmeter

ref-03/2009



**AJC Power Solutions**  
**Unit 10, Cosgrove Way,**  
**Luton, Bedfordshire,**  
**England LU11XL**

Tel: **+44 (0) 1582 486663**  
 email: **info@ajcpowersolutions.co.uk**  
 website: **www.ajcpowersolutions.co.uk**